

Medicare Current Beneficiary Survey

Section Specifications for ENS

ENUMERATION SUMMARY

ROUND 70

Created on 4/29/2015

BOX ENSBEG

BOX INSTRUCTIONS

GO TO ENSINTRO - ENSINT.

OTHER PROGRAMMING INSTRUCTIONS

BACKGROUND VARIABLE ASSIGNMENTS

Enumeration Summary reviews who lived in the household at the time of the previous round interview and determines who still lives in the household in the current round. Enumeration Summary also probes for new household members in the current round.

In order to collect current round household information, a current round ENUM record is generated for each person, including SP, who lived in the household at the time of the previous round interview. If MRES.INTTYPE = 2/NewFromFacility, 3/NewFromSupplement, 5/LastRndFacSum, 6/LastRndFacBase, only create a current round ENUM for the SP. Since the SP did not have a community interview in the previous round, there will be no persons reported as living in the household in the previous round.

ENUM Key = ENUM.ENUMBASE + ENUM.ENUMROST + ENUM.ENUMRND.

ENUM.ENUMROST = ROST.ROSTNUM of person who lived in the household in the previous round.

ENUM.ENUMRND = current round.

When creating the current round ENUM records, populate the person's name, relationship to SP, gender, and date of birth from ROST.

Use the following logic to calculate the Household member's age stored on ENUM.HHPAGE:

If calculating SP's age then:

If SP is deceased, calculate AGE based on SP's date of birth, ROST.HHDOBMM, ROST.HHDOBDD, ROST.HHDOBYYY, and the SP's date of death, MRES.SPDIEMM, MRES.SPDIEDD, MRES.SPDIIEYY.

Else if SP is institutionalized, calculate AGE based on SP's date of birth, ROST.HHDOBMM, ROST.HHDOBDD, ROST.HHDOBYYY, and the SP's date of institution, MRES.SPINSTMM, MRES.SPINSTDD, MRES.SPINSTYY.

Else calculate SP's AGE based on their date of birth, ROST.HHDOBMM, ROST.HHDOBDD, ROST.HHDOBYYY, and the date of the interview.

If calculating other Household member's age then calculate AGE based on their date of birth, ROST.HHDOBMM, ROST.HHDOBDD, ROST.HHDOBYYY, and the date of the interview. If any part of the Household member's age is missing and AGE cannot be calculated, set current

round ENUM.HHPAGE = previous round ENUM.HHPAGE.

Set other fields on ENUM as instructed below. Copy ROST variables to ENUM where ENUM.ENUMROST= person's ROST.ROSTNUM.

Variable Name	Assignment Instructions
ENUMROST	Create ENUM where ENUM.ENUMROST=ENUM.ENUMROST for person who lived in the household at the time of the previous round interview.
ENUMRND	ENUM.ENUMRND = current round.
ENUMFNAM	ENUM.ENUMFNAM = ROST.ROSTFNAM.
ENUMLNAM	ENUM.ENUMLNAM = ROST.ROSTLNAM.
HHPREL	ENUM.HHPREL = ROST.ROSTREL.
HHPRELOS	ENUM.HHPRELOS = ROST.ROSTREOS.
HHPSEX	If ROST.ROSTSEX = empty, set ENUM.HHPSEX=DK. Else if ROST.ROSTSEX = 1/Male or 2/Female, set ENUM.HHPSEX = ROST.ROSTSEX. Else if set ENUM.HHPSEX = previous round ENUM.HHPSEX.
EHHDOBMM	ENUM.EHHDOBMM = ROST.HHDOBMM.
EHHDOBDD	ENUM.EHHDOBDD = ROST.HHDOBDD.
EHHDOBY	ENUM.EHHDOBY = ROST.HHDOBY.
HHPAGE	Calculate HHPAGE. (see instructions above). If any part of person's date of birth is missing and AGE cannot be calculated, set current round ENUM.HHPAGE = previous round ENUM.HHPAGE.

ENSINTRO

No Entry

QUESTION TEXT

Now I'd like to [review with you who was living in the household/ask you a few questions about [your/(SP's)] home and any other people who may live in the household.].

FIELD 1: ENSINT**FIELD 1 ROUTING**

Value	Label	Route
1	CONTINUE	BOX ENS1
	Empty	BOX ENS1

FIELD 1 ATTRIBUTES

Cheshire Name	Answers Allowed
TEMP	1

BOX ENS1

BOX INSTRUCTIONS

IF AT LEAST ONE PERSON LIVED IN THE HOUSEHOLD WITH THE SP AT THE TIME OF THE PREVIOUS ROUND INTERVIEW, GO TO ENS1 - HHSTILL.

ELSE GO TO ENS3 - HHNEW.

OTHER PROGRAMMING INSTRUCTIONS

DESIGN NOTES

If MRES.INTTYPE = 2/NewFromFacility, 3/NewFromSupplement, 5/LastRndFacSum, 6/LastRndFacBase, there will be no one reported as living in the household in the previous round.

If SP was the only household member at the time of the previous round interview, there will only be one ENUM where ENUM.ENUMRND=previous round and that ENUM.ENUMROST will equal '01' for the SP.

If SP is the only person who lived in the HH in the previous round, or MRES.INTTYPE = 2/NewFromFacility, 3/NewFromSupplement, 5/LastRndFacSum, 6/LastRndFacBase, go to ENS3.

ENS1

Yes/No

QUESTION TEXT

From our last interview on (REFERENCE DATE), we have listed that [(READ NAME(S) LISTED BELOW)] lived in the same household as [you/(SP)].

[As of (DATE OF DEATH/DATE OF INSTITUTIONALIZATION), did/Do/Does] [READ NAME(S) LISTED BELOW] still live in the same household as [you/(SP)]?

[A SEPARATE QUESTION WILL ASK YOU IF ANYONE ELSE SHOULD BE ADDED. THIS QUESTION ONLY REFERS TO THE LISTED PERSONS.]

FIELD 1: HHSTILL**FIELD 1 ROUTING**

Value	Label	Route
1	YES	ENS3 - HHNEW
2	NO	ENS2 - HOUSEHOLD_NOT
	Don't Know	ENS3 - HHNEW
	Refused	ENS3 - HHNEW

FIELD 1 ATTRIBUTES

Cheshire Name	Answers Allowed
HRND.HHSTILL	1

OTHER PROGRAMMING INSTRUCTIONS**REPORT DISPLAY**

Display report below question text.

Display all persons who lived in the household at the time of the previous round interview.

Do not display SP, where ENUM.ENUMROST=01.

Display all other household members in the order that they were entered in the Person Roster.

Report Header: HOUSEHOLD MEMBERS AS OF (REFERENCE DATE)

COL 1, header = "First Name", display ENUM.ENUMFNAM.

COL 2, header = "Last Name", display ENUM.ENUMLNAM.

ENS2

Roster

QUESTION TEXT

PROBE FOR AND SELECT THOSE PEOPLE WHO ARE NO LONGER IN THE HOUSEHOLD.

FIELD 1: HOUSEHOLD NOT

FIELD 1 ROUTING

Value	Label	Route
1	[Continuous answer.]	ENS2_IN - NAVIGATOR

FIELD 1 ATTRIBUTES

Cheshire Name	Answers Allowed
TEMP	1

OTHER PROGRAMMING INSTRUCTIONS

ROSTER/GRID INSTRUCTIONS

Display all persons who lived in the household at the time of the previous round interview.

Display SP on first line, where ENUM.ENUMROST=01.

If Proxy interview and Proxy lived in the household at the time of the previous round interview, display Proxy on the second line, where ENUM.ENUMROST=MRES.RROSTNUM.

Display all other household members in the order that they were entered in the Person Roster.

Display the following as protected rows:

- 1) The SP.

ROSTER/GRID DISPLAY

Column #	Header	Instructions
1	First Name	Display ENUM.ENUMFNAM.
2	Last Name	Display ENUM.ENUMLNAM.

Column #	Header	Instructions
3	Relationship to SP	Display relationship: If ENUM.HHPREL=91/OtherRelative or 92/OtherNon-Relative, display ENUM.HHPRELOS. Else display ENUM.HHPREL relationship.

BACKGROUND VARIABLE ASSIGNMENTS

Roster details will be collected on ENUM:

ENUM key = ENUM.ENUMBASE + ENUM.ENUMROST + ENUM.ENUMRND.

ENUM.ENUMROST = ROST.ROSTNUM of person selected at ENS2.

ENUM.ENUMRND = current round.

ENS2_IN

Instance Navigator

FIELD 1: NAVIGATOR

FIELD 1 ROUTING

Value	Label	Route
1	ITEM SELECTED IN INSTANCE NAVIGATOR	ENS2A - NOTHHRSN
2	CONTINUE INTERVIEW SELECTED	ENS3 - HHNEW

FIELD 1 ATTRIBUTES

Cheshire Name	Answers Allowed
N/A	1

OTHER PROGRAMMING INSTRUCTIONS

BACKGROUND VARIABLE ASSIGNMENTS

Roster details will be collected on ENUM:

ENUM key = ENUM.ENUMBASE + ENUM.ENUMROST + ENUM.ENUMRND.

ENUM.ENUMROST = ROST.ROSTNUM of person selected at ENS2.

ENUM.ENUMRND = current round.

ENS2A

Code 1

QUESTION TEXT

Why (is/was) (HOUSEHOLD MEMBER NAME) no longer in the household [as of (DATE OF DEATH/DATE OF INSTITUTIONALIZATION)]?

FIELD 1: NOTHRSN**FIELD 1 ROUTING**

Value	Label	Route
1	DECEASED	BOX ENS2
2	INSTITUTIONALIZED, HEALTH CARE FACILITY	BOX ENS2
3	INSTITUTIONALIZED, OTHER	BOX ENS2
4	PERSON MOVED	BOX ENS2
5	SP MOVED	BOX ENS2
6	PERSON NOT IN HOUSEHOLD - PREVIOUS ROUND ERROR	BOX ENS2
91	OTHER REASON	ENS2A - NOTHHROS
	Don't Know	BOX ENS2
	Refused	BOX ENS2

FIELD 1 ATTRIBUTES

Cheshire Name	Answers Allowed
ENUM.NOTHRSN	1

FIELD 2: NOTHHROS

OTHER REASON (SPECIFY)

FIELD 2 ROUTING

Value	Label	Route
1	[Continuous answer.]	BOX ENS2

FIELD 2 ATTRIBUTES

Cheshire Name	Answers Allowed
ENUM.NOTHHROS	1

BOX ENS2

BOX INSTRUCTIONS

GO TO ENS2_IN - NAVIGATOR.

ENS3

Yes/No

QUESTION TEXT

[(At the time of the last interview, [you were living by yourself/(SP) was living by (himself/herself)].)]

[Besides [you/(SP)], (is/was)] there anyone else living or staying in the household [as of (DATE OF DEATH/DATE OF INSTITUTIONALIZATION)]? Remember to include people who (are/were) temporarily absent and any children who (may live/may have lived) in the household.

FIELD 1: HHNEW**FIELD 1 ROUTING**

Value	Label	Route
1	YES	ENS4 - HOUSEHOLD_ENS
2	NO	BOX ENS4
	Don't Know	BOX ENS4
	Refused	BOX ENS4

FIELD 1 ATTRIBUTES

Cheshire Name	Answers Allowed
HRND.HHNEW	1

ENS4

Select one

QUESTION TEXT

[Who else (is/was) living or staying in the household?]

SELECT OR ADD ALL PERSONS LIVING IN THE HOUSEHOLD.

FIELD 1: HOUSEHOLD ENS**FIELD 1 ROUTING**

Value	Label	Route
1	[Continuous answer.]	ENS4A – HHMISS
2	NO ONE ELSE LIVING IN HOUSEHOLD	ENS4A – HHMISS

FIELD 1 ATTRIBUTES

Cheshire Name	Answers Allowed
TEMP	1

OTHER PROGRAMMING INSTRUCTIONS**ROSTER/GRID INSTRUCTIONS**

Display all persons from Person Roster.

Display SP on first line, where ROST.ROSTNUM=01.

If Proxy interview, display Proxy on second line, where ROST.ROSTNUM=MRES.RROSTNUM.

Display remaining persons in the order that they were entered in Person Roster.

Display the following persons as protected rows:

- 1) The SP.
- 2) All persons who have already been identified as living in the household in the current round.
- 3) All persons who have already been identified as no longer living in the household in the current round.
- 4) All persons who have already been identified as no longer living in the household because they are deceased.

ROSTER/GRID DISPLAY

Column #	Header	Instructions
1	First Name	Display ROST.ROSTFNAM
2	Last Name	Display ROST.ROSTLNAM.
3	Relationship to SP	Display relationship: If ROST.ROSTREL=91/OtherRelative or 92/OtherNon_Relative, display ROST.ROSTREOS. Else display ROST.ROSTREL relationship.
4	In Household	If there is a current round ENUM for person and ENUM.NOTHHRSN=empty, display "YES". Else If there is a current round ENUM for this person and ENUM.NOTHHRSN ^= empty, display "NO". Else if person just added, display "YES". Else do not display.

BACKGROUND VARIABLE ASSIGNMENTS

Roster details will be collected on ROST and ENUM:
 ROST key = ROST.ROSTBASE + ROST.ROSTNUM
 ROST.ROSTNUM = Number of person selected at ENS4.

ENUM key = ENUM.ENUMBASE + ENUM.ENUMROST + ENUM.ENUMRND.
 ENUM.ENUMROST = ROST.ROSTNUM of person selected at ENS4.
 ENUM.ENUMRND = current round.

If Person added, see PERSON ROSTER POP-UP specifications for pop-up window programming instructions.

Variables populated in Person Roster:
 ROST.ROSTNUM
 ROST.ROSTRNDC
 ROST.ROSTFNAM

ROST.ROSTLNAM
ROST.ROSTREL
ROST.ROSTREOS

If Person is edited, the following fields may be updated. See Person Roster Pop-Up Specifications for details.

ROST.ROSTSEX
ROST.ROSTEOS

Set reason for person added to roster. See instructions below.

Create a current round ENUM for any person selected at ENS4 as a new household member. Create ENUM where ENUM.ENUMRND=current round and EUM.ENUMROST=ROST.ROSTNUM of person selected.

ENUM key = ENUM.ENUMBASE + ENUM.ENUMROST + ENUM.ENUMRND.

The household member's name and relationship to SP is copied to the current round ENUM record from ROST.

Set variables as specified below:

Copy ROST variables to ENUM where ENUM.ENUMROST= person's ROST.ROSTNUM.

See detailed instructions below.

Variable Name	Assignment Instructions
ENUMROST	ENUM.ENUMROST = ROST.ROSTNUM.
ENUMRND	ENUM.ENUMRND = current round.
ENUMFNAM	ENUM.ENUMFNAM = ROST.ROSTFNAM.
ENUMLNAM	ENUM.ENUMLNAM = ROST.ROSTLNAM.
HHPREL	ENUM.HHPREL = ROST.ROSTREL.
HHPRELOS	ENUM.HHPRELOS = ROST.ROSTREOS.
HHPSEX	ENUM.HHPSEX = ROST.ROSTSEX.
EHHDOBMM	ENUM.EHHDOBMM = ROST.HHDOBMM.
EHHDOBDD	ENUM.EHHDOBDD = ROST.HHDOBDD.

Variable Name	Assignment Instructions
EHHDOBYY	ENUM.EHHDOBYY = ROST.HHDOBYY.
ROSTREAS	If person added to person Roster, set ROST.ROSTREAS = 3/InHousehold.

ENS4A

Yes/No

QUESTION TEXT

Now I want to make sure I have everyone who (lives/lived) in the household [as of (DATE OF DEATH/DATE OF INSTITUTIONALIZATION)]. I have listed [READ NAME(S) LISTED BELOW].

Have I missed any lodgers, boarders, or anyone else who usually (lives or stays/lived or stayed) in the household but (is/was) away from home traveling or in the hospital?

FIELD 1: HHMISS**FIELD 1 ROUTING**

Value	Label	Route
1	YES	ENS4 - HOUSEHOLD_ENS
2	NO	ENS5 - HHPSEX
	Don't Know	ENS5 - HHPSEX
	Refused	ENS5 - HHPSEX

FIELD 1 ATTRIBUTES

Cheshire Name	Answers Allowed
HRND.HHMISS	1

OTHER PROGRAMMING INSTRUCTIONS**REPORT DISPLAY**

Display report below question text.

Display all person's identified as a household member this round.

Display SP on first line, where ENUM.ENUMROST= 01.

If proxy interview and proxy lives in the household in the current round, display the proxy on the second line, where ENUM.ENUMROST=MRES.RROSTNUM (Proxy's ROST.ROSTNUM).

Display remaining household members in the order they were entered in the Person Roster.

Report header: CURRENT HOUSEHOLD MEMBERS

Report layout:

Column 1, header = "First Name", display ENUM.ENUMFNAM.

Column 2, header = "Last Name", display ENUM.ENUMLNAM.

ENS5

Grid

FIELD 1: HHPSEX

Is (HOUSEHOLD MEMBER NAME) male or female?

FIELD 1 ROUTING

Value	Label	Route
1	MALE	ENS5 - EHHDOBMM
2	FEMALE	ENS5 - EHHDOBMM
	Don't Know	ENS5 - EHHDOBMM
	Refused	ENS5 - EHHDOBMM

FIELD 1 ATTRIBUTES

Cheshire Name	Answers Allowed
ENUM.HHPSEX	1

FIELD 2: EHHDOBMM

What is (HOUSEHOLD MEMBER NAME'S) date of birth?

[ENTER DATE.]

FIELD 2 ROUTING

Value	Label	Route
1	[Continuous answer.]	ENS5 - EHHDOBDD
	Don't Know	ENS5 - EHHDOBDD
	Refused	ENS5 - EHHDOBDD

FIELD 2 ATTRIBUTES

Cheshire Name	Answers Allowed
ENUM.EHHDOBMM	1

FIELD 3: EHHDOBDD

What is (HOUSEHOLD MEMBER NAME'S) date of birth?
[ENTER DATE.]

FIELD 3 ROUTING

Value	Label	Route
1	[Continuous answer.]	ENS5 - EHHDOBYYY
	Don't Know	ENS5 - EHHDOBYYY
	Refused	ENS5 - EHHDOBYYY

FIELD 3 ATTRIBUTES

Cheshire Name	Answers Allowed
ENUM.EHHDOBDD	1

FIELD 4: EHHDOBYYY

What is (HOUSEHOLD MEMBER NAME'S) date of birth?
[ENTER DATE.]

FIELD 4 ROUTING

Value	Label	Route
1	[Continuous answer.]	BOX ENS4
	Don't Know	ENS5 - HHPAGE
	Refused	ENS5 - HHPAGE

FIELD 4 ATTRIBUTES

Cheshire Name	Answers Allowed
ENUM.EHHDOBY	1

FIELD 5: HHPAGE

How old is (HOUSEHOLD MEMBER NAME)?

FIELD 5 ROUTING

Value	Label	Route
1	[Continuous answer.]	BOX ENS4
	Don't Know	BOX ENS4
	Refused	BOX ENS4

FIELD 5 ATTRIBUTES

Cheshire Name	Answers Allowed
ENUM.HHPAGE	1

OTHER PROGRAMMING INSTRUCTIONS**ROSTER/GRID INSTRUCTIONS**

Display names of all persons who are new household members in the current round.

Display all new household members in the order that they were entered in the Person Roster.

ROSTER/GRID DISPLAY

Column #	Header	Instructions
1	Name	Display ENUM.ENUMFNAM + ENUM.ENUMLNAM. Display only.

Column #	Header	Instructions
2	Relationship to SP	Display relationship: If ENUM.HHPREL=91/OtherRelative or 92/OtherNon_relative, display ENUM.HHPRELOS. Else display ENUM.HHPREL relationship. Display only.
3	Gender	ENUM.HHPSEX. Input field 1.
4	Date of Birth	Display "Date of Birth" over columns 4, 5, 6. ENUM.EHHDOBMM. Input field 2.
7	Age	ENUM.HHPAGE. Input field 5.

BACKGROUND VARIABLE ASSIGNMENTS

Grid details will be collected on ENUM:

ENUM key = ENUM.ENUMBASE + ENUM.ENUMROST + ENUM.ENUMRND.

ENUM.ENUMROST = ROST.ROSTNUM of person data is being entered for at ENS5.

ENUM.ENUMRND = current round.

Household member's Gender, Date of Birth and Age are first collected at ENS5 into variables on the person's current round ENUM record. Gender and Date of Birth needs to be copied to the person's ROST record.

Set variables as specified below:

Copy ENUM variables to ROST where ROST.ROSTNUM = ENUM.ENUMROST.

Variable Name	Assignment Instructions
ROSTSEX	ROST.ROSTSEX = ENUM.HHPSEX.
HHDOBMM	ROST.HHDOBMM = ENUM.EHHDOBMM.
HHDOBDD	ROST.HHDOBDD = ENUM.EHHDOBDD.
HHDOBY	ROST.HHDOBY = ENUM.EHHDOBY.

BOX ENS4

BOX INSTRUCTIONS

IF AT LEAST ONE PERSON LIVING IN THE HOUSEHOLD WITH THE SP IN THE CURRENT ROUND, WAS ALSO LIVING IN THE HOUSEHOLD AT THE TIME OF THE PREVIOUS ROUND INTERVIEW AND (WAS MISSING ANY PART OF THEIR DATE OF BIRTH IN THE PREVIOUS ROUND) AND (HAS NEVER BEEN ASKED ENS10 IN ANY PREVIOUS ROUND), GO TO ENS10 - EHHDOBMM.

ELSE GO TO BOX ENS4A.

ENS10

Grid

QUESTION TEXT

ASK THE RESPONDENT TO PROVIDE INFORMATION FOR ALL "DK" AND "RF" ENTRIES LISTED BELOW. DO NOT CHANGE THE ENTRIES IF THE RESPONDENT STILL DOES NOT KNOW THE INFORMATION.

FIELD 1: EHHDOBMM

(HOUSEHOLD MEMBER NAME'S) DATE OF BIRTH.
[ENTER DATE.]

FIELD 1 ROUTING

Value	Label	Route
1	[Continuous answer.]	ENS10 - EHHDOBDD
	Don't Know	ENS10 - EHHDOBDD
	Refused	ENS10 - EHHDOBDD

FIELD 1 ATTRIBUTES

Cheshire Name	Answers Allowed
ENUM.EHHDOBMM	1

FIELD 2: EHHDOBDD

(HOUSEHOLD MEMBER NAME'S) DATE OF BIRTH.
[ENTER DATE.]

FIELD 2 ROUTING

Value	Label	Route
1	[Continuous answer.]	ENS10 - EHHDOBYY
	Don't Know	ENS10 - EHHDOBYY
	Refused	ENS10 - EHHDOBYY

FIELD 2 ATTRIBUTES

Cheshire Name	Answers Allowed
ENUM.EHHDOBDD	1

FIELD 3: EHHDOBY

(HOUSEHOLD MEMBER NAME'S) DATE OF BIRTH.
[ENTER DATE.]

FIELD 3 ROUTING

Value	Label	Route
1	[Continuous answer.]	ENS10 - HHPAGE
	Don't Know	ENS10 - HHPAGE
	Refused	ENS10 - HHPAGE

FIELD 3 ATTRIBUTES

Cheshire Name	Answers Allowed
ENUM.EHHDOBY	1

FIELD 4: HHPAGE

(HOUSEHOLD MEMBER NAME'S) AGE.

FIELD 4 ROUTING

Value	Label	Route
1	[Continuous answer.]	BOX ENS4A
	Don't Know	BOX ENS4A
	Refused	BOX ENS4A

FIELD 4 ATTRIBUTES

Cheshire Name	Answers Allowed
ENUM.HHPAGE	1

OTHER PROGRAMMING INSTRUCTIONS**ROSTER/GRID INSTRUCTIONS**

Display all persons living in the household with the SP in the current round, who was also living in the household at the time of the previous round interview and was missing any part of their date of birth in the previous round.

Do not display persons who have already been asked ENS10 in any previous round, where ROST.ENSFLAG=1/Yes.

Do not display the SP, where ENUM.ENUMROST=01.

If Proxy interview and Proxy meets the criteria above, display Proxy on the first line, where ENUM.ENUMROST=MRES.RROSTNUM (Proxy's ROST.ROSTNUM).

Display all remaining household members who meet the criteria above in the order that they were entered in the Person Roster.

ROSTER/GRID DISPLAY

Column #	Header	Instructions
1	Name	Display ENUM.ENUMFNAM + ENUM.ENUMLNAM. Display only.
2	Relationship to SP	Display relationship: If ENUM.HHPREL=91/OtherRelative or 92/OtherNon_Relative, display ENUM.HHPRELOS. Else display ENUM.HHPREL relationship. Display only.
3	Date of Birth	Display "Date of Birth" over columns 3, 4, 5. Display ENUM.EHHDOBMM. Input field 1 - Allow updates.

Column #	Header	Instructions
6	Age	Display ENUM.HHPAGE. Input field 4 - Allow updates.

BACKGROUND VARIABLE ASSIGNMENTS

Grid details will be collected on ENUM:

ENUM key = ENUM.ENUMBASE + ENUM.ENUMROST + ENUM.ENUMRND.

ENUM.ENUMROST = ROST.ROSTNUM of person data is being entered for at ENS10.

ENUM.ENUMRND = current round.

Household member's Date of Birth and Age are updated at ENS10 into variables on the person's current round ENUM record. If Date of Birth is changed at ENS10, copy updates to person's ROST record.

Copy ENUM variables to ROST where ROST.ROSTNUM = ENUM.ENUMROST. See detailed instructions below.

In addition, ENS10 is only asked once for any household member in any round. Set flag for each household member displayed at ENS10 indicating that ENS10 has been asked for that person. See instructions below.

Variable Name	Assignment Instructions
HHDOBMM	ROST.HHDOBMM = ENS10 - EHHDOBMM.
HHDOBDD	ROST.HHDOBDD = ENS10 - EHHDOBDD.
HHDOBYY	ROST.HHDOBYY = ENS10 - EHHDOBYY.
ENSFLAG	ROST.ENSFLAG = 1/Yes.

BOX ENS4A

BOX INSTRUCTIONS

IF (SP IS IN THE SUPPLEMENTAL SAMPLE) OR (SP'S PREVIOUS ROUND INTERVIEW WAS IN A FACILITY), GO TO BOX ENS4B.

ELSE GO TO BOX ENS5.

BOX ENS4B

BOX INSTRUCTIONS

IF AT LEAST ONE PERSON LIVES IN THE HOUSEHOLD WITH THE SP, GO TO ENS10A - HOUSEHOLD_OWNS.

ELSE SET SP AS PERSON WHO OWNS/RENTS HOME AND GO TO BOX ENS4C.

OTHER PROGRAMMING INSTRUCTIONS

BACKGROUND VARIABLE ASSIGNMENTS

If no one lives with the SP in the current round, set SP as person who owns home. See detailed instruction below.

Variable Name	Assignment Instructions
HHPOWN	If no one lives with the SP in the current round, set HRND.HHPOWN = '01'.

ENS10A

Roster

QUESTION TEXT

Who owns or rents [this/(SP's)] home? [PROBE: Of the people living (here/there) now, who is the person who is the head of the household?]

SELECT ONLY ONE.

FIELD 1: HOUSEHOLD OWNS

FIELD 1 ROUTING

Value	Label	Route
1	[Continuous answer.]	BOX ENS4C

FIELD 1 ATTRIBUTES

Cheshire Name	Answers Allowed
TEMP	1

OTHER PROGRAMMING INSTRUCTIONS

ROSTER/GRID INSTRUCTIONS

Display all persons identified as living in the household in the current round.

Display SP on first line, where ENUM.ENUMROST=01.

If proxy interview and proxy lives in the household in the current round, display the proxy on the second line, where ENUM.ENUMROST=MRES.RROSTNUM (Proxy's ROST.ROSTNUM).

Display remaining household members in the order they were entered in the Person Roster.

ROSTER/GRID DISPLAY

Column #	Header	Instructions
1	First Name	Display ENUM.ENUMFNAM.
2	Last Name	Display ENUM.ENUMLNAM.

Column #	Header	Instructions
3	Relationship to SP	Display relationship to SP: If ENUM.HHPREL=91/OtherRelative or 92/OtherNon-Relative, display ENUM.HHPRELOS. Else display ENUM.HHPREL relationship.

BACKGROUND VARIABLE ASSIGNMENTS

Set person selected at ENS10A as person who owns/rents home. See instructions below.

Variable Name	Assignment Instructions
HHPOWN	HRND.HHPOWN=ENUM.ENUMROST of person selected at EN6.

BOX ENS4C

BOX INSTRUCTIONS

IF (SP IS IN THE SUPPLEMENTAL SAMPLE) AND (SP'S AGE IS 16 OR OLDER, OR AGE = DK OR RF), GO TO ENS10AA - ASKWORK.

ELSE GO TO BOX ENS5.

ENS10AA

Yes/No

QUESTION TEXT

Since (REFERENCE DATE), did [you/(SP)] work at any time at a job or business?

FIELD 1: ASKWORK**FIELD 1 ROUTING**

Value	Label	Route
1	YES	BOX ENS5
2	NO	BOX ENS5
	Don't Know	BOX ENS5
	Refused	BOX ENS5

FIELD 1 ATTRIBUTES

Cheshire Name	Answers Allowed
TEMP	1

OTHER PROGRAMMING INSTRUCTIONS**BACKGROUND VARIABLE ASSIGNMENTS**

ENUM.HHPWORK is stored based on the response to ENS10AA.

Set variable as instructed below:

Set HHPWORK on ENUM where ENUM.ENUMRND=current round and ENUM.ENUMROST = '01'.

Variable Name	Assignment Instructions
HHPWORK	If ENS10AA - ASKWORK = 1/Yes, set ENUM.HHPWORK = 1/Works. Else if ENS10AA - ASKWORK = 2/No, set ENUM.HHPWORK = 2/DidNotWork. Else ENUM.HHPWORK = ENS10AA - ASKWORK.

BOX ENS5

BOX INSTRUCTIONS

IF (SP IS IN THE SUPPLEMENTAL SAMPLE AND ENS10AA - ASKWORK = 1/Yes) OR (IF SP IS NOT IN THE SUPPLEMENTAL SAMPLE AND ((IT IS A FALL ROUND) AND (SP IS ALIVE AND NOT INSTITUTIONALIZED) AND (SP'S AGE IS 16 OR OLDER, OR AGE = DK OR RF))), GO TO ENS11 - JOBSTAT.

ELSE GO TO BOX ENS5A.

ENS11

Yes/No

QUESTION TEXT

[Before I continue with the next set of questions, I need to collect information about [your/(SP's)] job status.] [Are you/ls (SP)] currently working at a job or business?

FIELD 1: JOBSTAT

FIELD 1 ROUTING

Value	Label	Route
1	YES	BOX ENS5A
2	NO	BOX ENS5A
	Don't Know	BOX ENS5A
	Refused	BOX ENS5A

FIELD 1 ATTRIBUTES

Cheshire Name	Answers Allowed
ENUM.JOBSTAT	1

BOX ENS5A

BOX INSTRUCTIONS

IF AT LEAST ONE PERSON WHO LIVES IN THE HOUSEHOLD WITH THE SP IS AGE 16 OR OLDER, OR AGE = DK OR RF AND ((THIS PERSON IS A NEW HOUSEHOLD MEMBER IN THE CURRENT ROUND) OR (IT IS A FALL ROUND)), GO TO ENS11A_IN - NAVIGATOR.

ELSE GO TO BOX ENS7.

OTHER PROGRAMMING INSTRUCTIONS

DESIGN NOTES

ENS11A - HHJBSTAT is asked only if Household member is AGE is 16 or older, or AGE = DK, RF.

ENS11A will be asked:

- 1) If the person is a new household member in the current round
- 2) If person was in the household at the time of the previous round interview, they will get ENS11A as an annual follow-up question only in the fall round.

BEGIN LOOP: Will ask ENS11A for each household member that meets this criteria.

ENS11A_IN

Instance Navigator

FIELD 1: NAVIGATOR

FIELD 1 ROUTING

Value	Label	Route
1	ITEM SELECTED IN INSTANCE NAVIGATOR	ENS11A - HHJBSTAT
2	CONTINUE INTERVIEW SELECTED	BOX ENS7

FIELD 1 ATTRIBUTES

Cheshire Name	Answers Allowed
N/A	1

OTHER PROGRAMMING INSTRUCTIONS

BACKGROUND VARIABLE ASSIGNMENTS

Details will be collected on ENUM:

ENUM key = ENUM.ENUMBASE + ENUM.ENUMROST + ENUM.ENUMRND.

ENUM.ENUMROST = ROST.ROSTNUM of person being asked about.

ENUM.ENUMRND = current round.

ENS11A

Yes/No

QUESTION TEXT

[Before I continue with the next set of questions, I need to update information about [your/(HOUSEHOLD MEMBER NAME'S)] job status.] [Are you/Is (HOUSEHOLD MEMBER NAME)] currently working at a job or business?

FIELD 1: HHJBSTAT**FIELD 1 ROUTING**

Value	Label	Route
1	YES	BOX ENS6
2	NO	BOX ENS6
	Don't Know	BOX ENS6
	Refused	BOX ENS6

FIELD 1 ATTRIBUTES

Cheshire Name	Answers Allowed
ENUM.HHJBSTAT	1

BOX ENS6

BOX INSTRUCTIONS

GO TO ENS11A_IN - NAVIGATOR.

BOX ENS7

BOX INSTRUCTIONS

IF ((SP IS IN THE SUPPLEMENTAL SAMPLE) OR (SP IS NEW FROM THE FACILITY)) AND SP'S AGE IS 17 OR OLDER OR AGE = DK OR RF, GO TO ENS12 - SPAFEVER.

ELSE GO TO BOX ENSEND.

ENS12

Yes/No

QUESTION TEXT

Now we have a few questions about military service.

Did [you/(SP)] ever serve in the Armed Forces of the United States?

FIELD 1: SPAFEVER**FIELD 1 ROUTING**

Value	Label	Route
1	YES	ENS13 - SPAFTIME
2	NO	ENS14 - SPNGEVER
	Don't Know	ENS14 - SPNGEVER
	Refused	ENS14 - SPNGEVER

FIELD 1 ATTRIBUTES

Cheshire Name	Answers Allowed
HOME.SPAFEVER	1

ENS13

Code All

QUESTION TEXT

SHOW CARD ENS 1

Looking at this card, in which of these time periods did [you/(SP)]
serve in the Armed Forces?

CHECK ALL THAT APPLY.

FIELD 1: SPAFTIME**FIELD 1 ROUTING**

Value	Label	Route
7	IRAQ OR AFGHANISTAN CONFLICT (2001-present)	ENS14 - SPNGEVER
6	PERSIAN GULF WAR (Aug 1990 - March 1991)	ENS14 - SPNGEVER
1	VIETNAM ERA (Aug 1964 - May 1975)	ENS14 - SPNGEVER
2	KOREAN CONFLICT (June 1950 - Jan 1955)	ENS14 - SPNGEVER
3	WORLD WAR II (Sept 1940 - July 1947)	ENS14 - SPNGEVER
4	WORLD WAR I (1917 - 1918)	ENS14 - SPNGEVER
5	PEACE TIME (ALL OTHER TIMES)	ENS14 - SPNGEVER
	Don't Know	ENS14 - SPNGEVER
	Refused	ENS14 - SPNGEVER

FIELD 1 ATTRIBUTES

Cheshire Name	Answers Allowed
NONE REPLACES CHESHIRE VARIABLE NAMES: 1/VietnamEra = HOME.SPAFVIET 2/KoreanConflict = HOME.SPAFKORE 3/WW2 = HOME.SPAFWWII 4/WW1 = HOME.SPAFWWI 5/PeaceTime = HOME.SPAFPEAC 6/PersianGulfWar = HOME.SPAFGULF 7/IraqAfghanConflict = HOME.SPAFIRAF	7

ENS14

Yes/No

QUESTION TEXT

[Were you/Was (SP)] ever an active member of a National Guard or military reserve unit of the United States?

FIELD 1: SPNGEVER

FIELD 1 ROUTING

Value	Label	Route
1	YES	ENS15 - SPNGALL
2	NO	BOX ENS14
	Don't Know	BOX ENS14
	Refused	BOX ENS14

FIELD 1 ATTRIBUTES

Cheshire Name	Answers Allowed
HOME.SPNGEVER	1

BOX ENS14

BOX INSTRUCTIONS

IF ENS12 - SPAFEVER = 1/Yes, GO TO ENS16 - SPNGDSBL.

ELSE GO TO BOX ENSEND.

ENS15

Yes/No

QUESTION TEXT

Was all of [your/(SP's)] active duty related to National Guard or military reserve training?

FIELD 1: SPNGALL

FIELD 1 ROUTING

Value	Label	Route
1	YES	ENS16 - SPNGDSBL
2	NO	ENS16 - SPNGDSBL
	Don't Know	ENS16 - SPNGDSBL
	Refused	ENS16 - SPNGDSBL

FIELD 1 ATTRIBUTES

Cheshire Name	Answers Allowed
HOME.SPNGALL	1

ENS16

Yes/No

QUESTION TEXT

[Do you/Does (SP)/Did (SP)] have a disability related to service in the Armed Forces of the United States?

[PROBE: 'Have you received a V.A. disability rating?' IF THE RESPONDENT HAS A V.A. DISABILITY RATING, SELECT "YES"; IF HE OR SHE DOES NOT, SELECT "NO"]

FIELD 1: SPNGDSBL

FIELD 1 ROUTING

Value	Label	Route
1	YES	ENS17 - SPVARATE
2	NO	BOX ENSEND
	Don't Know	BOX ENSEND
	Refused	BOX ENSEND

FIELD 1 ATTRIBUTES

Cheshire Name	Answers Allowed
HOME.SPNGDSBL	1

ENS17

Numeric

QUESTION TEXT

What [is [your/(SP's)]/was (SP's)] (current) V.A. disability rating?

THE VA DISABILITY RATING IS A PERCENTAGE IN MULTIPLES OF 10 (I.E., 10%, 20%, ETC.). ENTER THE NUMBER AS A WHOLE NUMBER. YOU DO NOT NEED TO ENTER THE "%" SIGN.

FIELD 1: SPVARATE

FIELD 1 ROUTING

Value	Label	Route
1	[Continuous answer.]	BOX ENSEND
	Don't Know	BOX ENSEND
	Refused	BOX ENSEND

FIELD 1 ATTRIBUTES

Cheshire Name	Answers Allowed
HOME.SPVARATE	1

BOX ENSEND

BOX INSTRUCTIONS

GO TO NEXT SECTION